

# Specifications

## TZY31 InstaShare Button Solution

### TWY31 InstaShare Button



#### Compatibility

1. RM03 series (with USB Type-C)  
2. RP02, RE01, RM02K, RM02S, CP01K, CS01, SL02K series, and VC01A (with USB Type-C to USB Type-A adapter)

Color	Silver
Wireless Transmission Frame Rate	Up to 60 fps depending on environment(1080P60/4K30P)
TX Button Input resolution	Up to 4K30P
Audio Rate	Stereo, Radio quality 16bits 48KHz
Wi-Fi Standard	IEEE 802.11ac 5GHz, 2T2R MIMO
Authentication protocol	Wi-Fi Standard
Wireless Security (Encryption)	WPA2/3 Personal/WPA2 Enterprise Support AES-256
Wireless Coverage Reach	Max. 15 m (Between Button and IFP)
Cable	USB Type C
Power Supply	DC 5V±10%, Minimum 0.9A
Power Consumption	Max 4.5W Full Loading
Dimension (WxHxD)	67mm x 67mm x23.2mm
Temperature range	Operating: 0°C to +40°C (+32°F to +104°F) Storage: -10°C to +60°C (+14°F to +140°F)
Humidity range	Operating: 10% to 80% relative humidity Storage: 5% to 90% relative humidity (non-condensing)

### TDY31 BenQ Wireless USB Dongle



#### Compatibility

RM03, RP02, RE01, RM02K, RM02S, CP01K, CS01, SL02K, ST02, ST02S, IL01, BH01, BH01T, BH01N, BH01D series, and VC01A

Color	Black
Wi-Fi Standard	802.11 a/b/g/n/ac
Interface	USB 3.0
Wi-Fi band	Dual Band 2.4GHz / 5GHz
MU-MIMO	Yes
Wi-Fi Performance	2.4 GHz Band: up to 400 Mbps 5 GHz Band: up to 867 Mbps
External Antenna	2
Supported OS	Android
Wireless Coverage Reach	Max. 15 m (Between Dongle and IFP)
Security	WPA-PSK/WPA2-PSK WPA/WPA2/WEP
Power Supply	DC 5V, 0.9A (Maximum)
Dimension L*H*W	137 x 41 x 12 mm
Net Weight	0.055kg
Temperature range	Operation : 0°C~40°C Storage : -40°C~70°C
Humidity range	Operation : 10%~90% Storage : 5%~90%

### TCY31 BenQ InstaShare Dock



Color	Black
Weight (Net)	420 g
Dimension L*H*W	150 x 85 x 106 mm
"InstaShare Button Loading quantity"	4 pcs
Product material	PC+ABS & Aluminum alloy 6063 & Silica gel

# Engaging lessons are just one click away



<b>Headquarters</b> BenQ Corporation 16 Jihu Road, Neihsu, Taipei 114, Taiwan Tel : +886-2-2727-8899 Fax : +886-2-2656-2438	<b>Asia Pacific</b> BenQ Asia Pacific Corp. 12 Jihu Road, Neihsu, Taipei 114, Taiwan Tel : +886-2-2727-8899 Fax : +886-2-2656-2438	<b>China</b> BenQ (IT) Co., Ltd. 181 Zhuyuan Road, Suzhou New District, Suzhou, China Tel : +86-512-6807-8800 Fax : +86-512-6809-7010	<b>North America</b> BenQ America Corp. 3200 Park Center Drive, Suite 150 Costa Mesa, CA 92626 U.S.A Tel : +1-714-559-4900 Fax : +1-714-557-0200	<b>Europe</b> BenQ Europe B.V. Meerenakkerweg 1-17, 5652 AR Eindhoven, The Netherlands Tel : +31(0) 88-888-9200 Fax : +31(0) 88-888-9299	<b>Latin and Central America</b> BenQ Latin America Corp. 8200 N.W. 33 Street, Suite 301 Miami, FL 33122 U.S.A. Tel : +1-305-421 1200 Fax : +1-305-421 1201
--	---	--	--	--	---

© 2022 BenQ Corp. Specification may vary by region, please visit your local stores for details. Actual products features and specifications are subject to change without notice.

This material may include corporate names and trademarks of third parties which are the properties of the third parties respectively

Doc: PDP\_TZY31/TWY31/TDY31/TCY31\_IFP\_EN\_202202

## TZY31 InstaShare Button Solution




# One-click wireless screen sharing



## Display lesson content wirelessly

Wireless lesson materials on one display no matter the room or session for all devices. The transmitter is compatible with laptops, Mac OS, and Chrome OS.



## The perfect setup for hybrid learning

It allows for one-to-one display in a classroom or online from home. The transmitter can be used in a classroom or online from home.

Available in



## Convenient connectivity

The USB-C connection allows for a simple and seamless connection to Mac OS and Chrome OS. The transmitter is compatible with laptops, Mac OS, and Chrome OS.

USB-C type equipment and USB

The transmitter is compatible with laptops, Mac OS, and Chrome OS. The transmitter is compatible with laptops, Mac OS, and Chrome OS.


## Get the whole class involved

Increase engagement by allowing all students to view content on their own devices. The transmitter is compatible with laptops, Mac OS, and Chrome OS.




## Complete control with touchback

Experience a new way to interact with lessons and presentations. The transmitter is compatible with laptops, Mac OS, and Chrome OS.



## Flexible content sharing

Share content from your laptop, camera, photo, video, or microphone. The transmitter is compatible with laptops, Mac OS, and Chrome OS.



## Industry-leading connection quality

Enjoy smooth classes with no lag or disconnections. The transmitter is compatible with laptops, Mac OS, and Chrome OS.